This Page Is Inserted by IFW Operations and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

As rescanning documents will not correct images, please do not report the images to the Image Problems Mailbox.

THIS PAGE BLANK (USPTO)

Europäisches Patentamt

European Patent Office

Office européen des brevets



(11) EP 0 957 604 A1

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:

17.11.1999 Bulletin 1999/46

(51) Int. Ci

(51) Int. Cl.⁶: **H04J 11/00**, H04L 25/03,

H04B 7/216

(21) Application number: 98108906.3

(22) Date of filing: 15.05.1998

(84) Designated Contracting States:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU

MC NL PT SE

Designated Extension States:

AL LT LV MK RO SI

(71) Applicant:

Sony International (Europe) GmbH 50829 Köln (DE)

(72) Inventors:

- Stirling-Gallacher, Richard 70736 Fellbach (DE)
- Jürgensen, Jens-Uwe 70736 Fellbach (DE)

(74) Representative:

Rupp, Christian, Dipl.Phys. et al Mitscherlich & Partner Patent- und Rechtsanwälte Sonnenstrasse 33 80331 München (DE)

(54) Transmitter and transmitting method increasing the flexibility of code assignment

(57)According to the present invention a transmitter and a transmitting method for communicating data symbols over a communication channel, for example, according to the CDMA system is presented. The transmitter (24, 25) comprises means (9) for spreading each data symbol with a respective spreading code, wherein the spreading codes are mutually orthogonal. Means (10) for scrambling are provided to scramble each spread symbol with a respective scrambling code, the scrambling codes respectively having the same length as the spreading codes. Furthermore, means (11) for the transmission of the spread and scrambled symbols are provided. According to the present invention the means (10) for scrambling are provided with a plurality of different scrambling codes, which can be used simultaneously within the same link.

The main advantages of the present invention are the greater flexibility in the assignment of spreading sequences within a CDMA system, the increased maximum data rate for downlink or uplink.




Fig. 2

FP 0 957 604 A1

Description (C. F. Jan.) Skill make the condition of the condition

[0001] The present invention relates to a transmitter, a wireless transmission system as well as to a method, for the transmission of data symbols over a communication channel which particularly finds its application in the field of so-called CDMA systems.

1..

[0002] CDMA (Code Division Multiple Access) transmitting systems are known from the state of the art. According to one CDMA technique, after the modulation (symbol mapping), the symbols are spread by a so-called spreading sequence or spreading code. After spreading the resulting data stream is scrambled by a scrambling sequence of a scrambling code. The thus resulting data stream, which has been spread and 15 scrambled, is then power-amplified and sent over a communication channel. The reverse procedure happens at the receiving side.

[0003] In Figure 3 an example for a transmission system comprising scrambling and spreading is shown. In 20. the example of Figure 3 only the downlink communication channel 26 from a base station 24 to a mobile station, 25 is shown. The downlink 26 can comprise different channels D₁,...., D_N. Each channel comprises channelisation (spreading) 28, 30 and scrambling 29, 31. According to the state of the art in one link, as for example the downlink 26 as shown in Figure 3, only one scrambling sequence (scrambling code) and several different spreading codes (often referred to as channelization codes) are used depending upon the data rate and services required. The drawback of this approach is that only certain types of channelisation codes can be used together and the highest data rate is constrained by the length of the shortest channelisation code. This is especially true when codes of different rates are used.

[0004] From W096/05668 A1 and EP-A-565 506 techniques for multiple access coding for radio communication is known, According to these documents. information symbols are spread using orthogonal or biorthogonal codewords. This spread information symbols are assigned a unique scramble mask that is taken from a set of scramble masks having selected correlation properties. The set of scramble masks is selected such that the correlation between the modulo-2 sum of two scramble masks with any codeword is a constant magnitude independent of the codeword and the individual mask being compared. According to one embodiment of WO 96/05668 A1, when any two masks are summed using modulo-2 sum arithmetic, the Walsh transformation of that sum results in a maximally flat Walsh spectrum. For cellular radio telephone systems using subtractive CDMA demodulation techniques, a two-tier ciphering system ensures security at the cellular system level by using a pseudorandomly generated code key to select one of the scramble masks common to all of the mobile stations in a particular cell. As according to these techniques one common scramble mask is used for all mobile stations in a particular cell,

the above-cited drawback arises that only certain types of channelisation codes can be used together limiting the number of available channelisation (spreading) codes.

[0005] In view of the above-cited drawbacks it is of the object of the present invention to enhance the flexibility of code assignment for a CDMA system, particularly within a cell sector and/or to increase the maximum data rate.

[0006] The central idea of the present invention thereby is a new code allocation scheme for a CDMA system utilising two or more scrambling codes within one link (uplink or downlink).

[0007] According to the present invention therefore a transmitter for communicating data symbols over a communication channel is provided, the transmitter comprising means for spreading each data symbol with a respective spreading code, wherein the spreading codes are mutually orthogonal. Furthermore means for scrambling each spread symbol with a respective scrambling code are provided, the scrambling, codes respectively having the same length as the spreading codes. Means are provided for the transmission of the spread and scrambled symbols. According to the present invention the means for scrambling are provided with a plurality of different scrambling codes which can be used simultaneously within the same link.

[0008] The means for scrambling the spread symbols can use different scrambling codes for an uplink communication channel and a downlink communication channel.

[0009] The spreading codes can be obtained by means of a code tree.

[0010] According to an aspect of the present invention, only in a downlink communication channel different scrambling codes are used, wherein in an uplink channel only one scrambling code is used.

[0011] The means for scrambling can use different scrambling codes within the same link only for channels demanding a high bit rate.

[0012] According to the present invention, furthermore a wireless transmission system comprising a transmitter of the above-cited type is provided, wherein a subset of scrambling codes is respectively allocated to a cell of the transmission system.

[0013] Different spreading codes can be allocated to adjacent cells of the transmission system.

[0014] According to the present invention, furthermore a method for the transmission of data symbols over a communication channel is provided. Data symbols are spread with a respective spreading code, wherein the respective spreading codes are mutually orthogonal. Each spread symbol is scrambled with a respective scrambling code, the scrambling codes not changing the band rate of the transmission (in contrast to the spreading codes). The spread and scrambled symbols are transmitted.

[0015] According to the present invention, when

scrambling a plurality of different scrambling codes can be used, which are to be used simultaneously within the same link.

[0016] In the step of scrambling the entiscrambling codes can be used for an upone communication channel and a downlink communication channel respectively.

[0017] The spreading cooper to the obtained by means of a code tree.

[0018] As an aspect of the process only in a 10 downlink communication of the process of the scrambling codes are used. In the use control only one scrambling code is the process of the

[0019] Different scrame of the same link only for the same link on the same

[0020] Particularly determine the same link can be used to a series within the same link can be used to a series within nels and/or data channels taken as a series within the same link can be used to a

[0021] Further aspects the present invention will not be a few to means of embodiments of the present frequency to the enclosed for a few to the enc

Figure 1 shows a community of the mission system according to the mission according to the missio

Figure 2 shows the great treety for a downlink communication channe the great and a mobile station of the great shown in Figure 1.

scrambling in a downer of the station according to the prior at

Figure 4 shows the country of the second of

Figure 5 shows an appearance of the provide to feece with the common of CDMA's systems, and

Figure 6 shows an application of the present invention to provide for higher data rate services.

[0022] A transmission system according to the present invention will now the experient generally with reference to Figure 1. As shown in Figure 1 different data can be transmitted in a sweless marrier. The data to be transmitted can comprise socie data from a telephone 1, 23, video data for example, from a video camera 5 to be transmitted to a month? 20 and other

information data, as for example, data from a computer -6 to be transmitted to another computer 19. The analog voice data from a telephone 1 are A/D-converted 2: voice coded 3 and then supplied to a channel encoder 4. The data, for example, from a video camera 5 or from the computer 6 are also supplied to the channel. encoder 4. The different data, for example, the voice data and the video data can be transmitted simultaneously. The data from the channel encoder 4 are given to 1 a interleaver 7 and then supplied to a modulator 8 providing for a symbol mapping. The modulated data from modulator 8 are then spread 9 and scrambled 10, which will be explained later on in detail." The spread and scrambled data are amplified 11, and then transmitted: over a wireless transmission path 12. On the receiving side the wireless transmitted data are down converted: 13; A/D-converted 14, descrambled 15 and despread. 16. The descrambling and the despreading will be also explained later on in detail. The descrambled and despread data are deinterleaved 17 and then supplied to a channel decoder 18. The channel decoder 18 outputs data to a computer 19, to a monitor 20 and/or a voice décoder 21. In case of voice data, the voicedecoded data 21 are D/A converted 22 and then supplied to a handset 23.

[0023] With reference to Figure 2, particularly the scrambling procedure according to the present invention will now be explained in detail.

[0024] In Figure 2 the communication between a base station 24 and a mobile station 25 is shown. Particularly the downlink channel 26 from the base station 24 to the mobile station 25 and the uplink channel 27 between the mobile station 25 and the base station 24 are shown. The downlink channel 26 and the uplink channel 27 comprise different subchannels D₁...D_N, D₁...D_N. A first subset of the subchannels of the downlink channel 26 can for example be used for voice data and other subchannels can be used for the simultaneous transmission of video data. The data from the base station 24 are channelised (spread) with different spreading codes C_{channel1},...,C_{channelN}, which are mutually orthogonal or bi-orthogonal 28, 30. The spread data are then scrambled 29, 31 with scrambling codes C_{scramble 1,...};C_{scram}: ble M. According to the present invention therefore scrambling codes which are different, but need not to be mutually orthogonal or bi-orthogonal, are used within the same link, for example, the downlink 26. (The orthogonality requirements are satisfied by the spreading codes.)

[0025] For the uplink 27, according to the present invention either the same scrambling codes C_{scramble} in the case of the downlink 26, or another group of scrambling codes C_{scramble} in the case of the downlink 26, or another group of scrambling codes C_{scramble} in C_{scramble} in the case of the downlink channel 27 demands for the same high bit rate as the downlink channel 26, even just one scrambling code can be used. [0026] As it has already been set forth above, the downlink channel 26 or the uplink channel 27 can com-

prise subchannels for video and/or voice transmission. As one aspect of the present invention, different scrambling codes can be allocated for the scrambling of the channels demanding for a high bit rate, as it is the case, for example, for the transmission of video data. For transmission of, for example, voice data, only one scrambling code can be used.

[0027]. Regarding the details of the spreading and scrambling process, particularly the modulo-2 sum operation for the scrambling at the transmission side and the multiplying operation for the descrambling at the reception side, the above-cited documents. WO 96/05668 A1 and EP-A-565 506 are incorporated by reference. Particularly Figures 1 and 2 in the corresponding description (page 14 to page 19) of WO 96/05668 A1 are incorporated by reference.

[0028] According to the present invention the spreading codes are generated by a code tree. This technique is known from Adachi, "Tree-structured generation of orthogonal spreading codes with different lengths for forward link of DS-CDMA mobile radio", Electronic Letters, January 1997, Vol:33, No.1, page 27, 28, which is incorporated herewith by reference.

[0029] Orthogonal spreading codes with different lengths can be generated by a tree-structure for orthogonal multiplexing of forward-link code-channels of different data rates in direct sequence code division multiple access DS-CDMA mobile radio. Thereby codes of the same layer of the tree constitute a set of Walsh functions and are orthogonal. Furthermore, any two codes of different layers of the tree structure are also orthogonal except for the case that one of the two codes is a mother code of the other.

[0030] As it has already been set forth in the introductory portion, when only one scrambling code (or long code) is used per link, there are restrictions of the combinations of codes which can be used for the orthogonal codes (see Adachi et al.) These restrictions may prevent a user from being allocated to a certain channel. These restrictions are especially important for high data rate users. Furthermore the highest data: rate is restricted to the shortest orthogonal code.

[0031] As according to the present invention, two or more scrambling codes are assigned to one link (one user), the following advantages are achieved:

increased flexibility in assignment of orthogonal codes since the data rate can be split over at least two scrambling codes and a different (longer) orthogonal code can be chosen from the code tree (see Adachi et al); and the highest data rate is increased since the data rate can be split over at least two scrambling codes. Therefore a higher data rate service on one link (uplink or downlink) can be provided by using a plurality of scrambling codes within one link. In this way the same channelisation codes (spreading codes) can be reused and a higher data rate can be

supported because the highest data rate is restricted, by the set of channelisation codes (spreading codes) with the shortest link.

និស្សាអាត្រស្_{សាស}្សាស្ត្រ A BOAR STATE 5 7 [0032] , By only using two scrambling codes (M=2) per link (user), the total number of available channelisation codes (spreading codes) can be doubled and the maximum data rate can also be doubled. The way to be also [0033] Figure 4 shows a symbolized cell distribution of a wireless transmission system. One cell C_1 is resurrounded by six other hexagonal cells C2,...,C7. According to the present invention; a total number of for example, 512 different scrambling codes can be used. To avoid interference between adjacent cells, the total number of 512 scrambling codes can for example be divided by 7 and each cell C1,..., C7 can be allocated a subset of said scrambling codes. Different users within one cell can use different scrambling codes allocated to the respective cell.

[0034] As it has already been set forth above, according to the present invention one scrambling code is used in conjunction (with a set of channelisation codes (spreading codes) depending upon the required data rate and services required. Adjacent base stations can use different scrambling codes and every base station uses (a set of scrambling codes to maintain different links in each cell.)

[0035] An application of the present invention will now be explained with reference to Figure 5. According to the state of the art, if a new user requests, for example, a 2 Mbit/s service, the base station 24 is forced to allocate a new scrambling code (and code tree) to support this service. The codes in the code tree are therefore not optimally utilised.

35. [0036] and To increase the flexibility of code assignment and increase the usage of the codes and the code tree, it is proposed to use as an option more than one scrambling code per link.
 [0037] In Figure 5 a base station 24 is shown using two scrambling sequences (codes) 1 and 2. Shown by

each scrambling sequences (codes) 1 and 2. Shown by each scrambling code is a set of possible services being supported by each of the scrambling codes. In this load situation, if a new user 32 requests a 2 Mbit/s service, the base station 24 has to devote a new scrambling code to support this service.

[0038] If, however, the new user 32 uses 2 (SF=4) orthogonal codes from scrambling code 1 and 1 (SF=4) orthogonal code from scrambling code 2, a 2 Mbit/s service can be supported and the codes and the code tree can be more optimally utilised.

[0039] Figure 6 shows another application of the present invention. According to Figure 6 the idea according to the present invention is used to provide an increased data rate for example, for a WCDMA system: Figure 6 shows the suggested scheme for an increased data rate. To increase the data rate normally in WCDMA one or both of the following approaches are required:

TARREST TOLLY STORY TO BE BUT WESTER OF

- 3 reduction of processing gain, and 35 increase of chip rate (enhanced bandwidth)

[0040] By utilizing the scheme as shown in Figure 6 the data rate can be increased by combining more than 5 one scrambling code. The example shows the data rate at 4 Mbit/s, but obviously higher rates can be achieved by using more than one scrambling code: See the Colors Claims Code was the second of the second of

- 1. Transmitter for communicating data symbols over a communication channel, the transmitter (24, 25) - comprising: From the two states and the comprising of the comprising of the compression of the compressio A TO B LEIDE TO BE LEVEL OF THE TOP 15
- i- means (9) for spreading each data symbol with ' a respective spreading code, wherein the spreading codes are mutually orthogonal, means (10) for scrambling each spread symbol " with a respective scrambling code, the scrambling codes respectively having the same length as the spreading codes, and a character in - means (11) for the transmission of the spread and scrambled symbols. The control of the control o wherein the means (10) for scrambling are pro-25 #73 at syided with a plurality of different scrambling codes which can be used simultaneously within a the same link.
- 2.5 Transmitter according to claim 1, 1998 1998 1998 of characterized in that work is the state of the control of the c
- the means for scrambling (10) can use different scrambling codes for an uplink communication 1 4 3 channel (27) and a downlink communication 35 channel (26), respectively. HOLDER TO SEE THE PROPERTY OF A SECRETARY TO

Andulary & Barger of Johnson Briston British of

3. Transmitter according to anyone of the preceding a claims, the man that the second and the second The characterized in that the second of the second of 40

ppが (おこりは) (Mar かり からに Hook にかりにつけばなかり) と

standing or repriled with thing of the profession of the

- the spreading codes are obtained by means of 67 York a code tree. I such a such a partie partie. gregorials, and the first of the first section
- 4. Transmitter according to anyone of the preceding ensichalmsgsmitten wird der eine einem mit der bestigt. -- characterized in that the control of the control 医维纳氏蛋白 医多种 化多种物的 人名英格兰人姓氏格特
- 145 60 only in a downlink communication channel (26) different scrambling codes are used, wherein in an uplink channel (27) only one scrambling: Roof, whoole is used the appropriate for the property of the pro-BY SECTION AND A SECTION ASSESSMENT OF COURSE OF SECTION 7
- 57 Transmitter according to anyone of the preceding To claims, and an import hereign, such as the interference full Characterized in that the track of the control of the following drawning sedbendage park in the fire of a
 - the means (10) for scrambling use different

- scrambling codes within the same link only for are channels demanding a high bit rate. the cares a seed of could
- 6. Transmitter according to claim 5, Characterized in that मुक्क कि उन्हर्भ कराइन है। के इस्त है है औ

5 18 AL THE LONG

the means for scrambling use different scram-7 bling codes within the same link only for video the Channels, with that the artists of the control of the section of . I kandim opila – z prem sa

1.00

- 7. Wireless transmission system, f characterized in that
 - Roman the rooms and the control of the -bittigait comprises a transmitter, (24,-25) according to ... ಕರೆಯಿ anyone of the preceding claims, wherein a sub-್ಯ set of scrambling codes is respectively allo- 6 cated to a cell of the transmission system.

eapert in the second our black of their congre


- 8. Wireless transmission system according to claim 7. Characterized in that the second of the second seco
 - the taken by two street AMD to be a local different spreading codes are allocated to adjacent cells of the transmission system. Proceedings Caratha color a la 1967 de 1967 de 1967
- 9. Method for the transmission of data symbols over a communication channel comprising the following TRISTEPS: The Avel Calebra (1997) and a second of the seco and home and in the court of will differ was
 - spreading (9) each data symbol with a respecwherein the spreading code, wherein the spreading HUTTER codes are mutually orthogonal, ARI MITTERS IN 8 - 9 scrambling (10) each spread symbol with a 9 respective scrambling code, the scrambling codes respectively having the same length as with the spreading codes, and the spreading codes, and -.. -> transmitting (1.1, 12) the spread and scrambled have go symbols, and so and the area of the results of the section of wherein for the step of scrambling (10) a pluralwill dity of different scrambling codes is used which

can be used simultaneously within the same-


Control of the Contro TOTAL MONTHS TO LONG MINISTRAL

- His characterized in that
- Employed the result of the second of the in the step of scrambling (10) different scram-. It is bling codes can be used for an uplink commu-the nication channel :: (27) and a downlink communication channel (26) respectively.
- LEADERCOING HOLDS SECTION AND A SECTION OF THE PARTY OF T 11. Method according to anyone of claims 9 or 10, she characterized in that with the control of the control alina at house of writers of those control for
- the spreading codes are obtained by means of and code tree.
- graph and the writing the extreme of the 12. Method according to anyone of claims 9 to 1:1; characterized in that

only in a downlink communication channel (26) different scrambling codes are used, wherein in the uplink communication channel (27) only one scrambling code is used; 13. Method according to anyone of clair characterized in that . . . different scrambling codes, are used only for channer bit rate. 14. Method according to claim to characterized in that' 15 different scrambling دع are used only for vide: 20 25 30 35 45 50 55



Ų








Fig. 4







EUROPEAN SEARCH REPORT

er waters of the proof

EP 98 10 8906

ategory	Citation of docume of relevant	int with indication, want passages	vhere appropriate,		Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.CI.5)
5,A ,	WO 96 05668 A 22 February 19 * abstract * * page 4, line * page 8. line	(ERICSSON GI	6, line 9 *	stati offis, (L)		H04J11/00 H04L25/03 H04B7/216
747 127 127 127 128 138 138 138 138 138 138 138 138 138 13	\$ 1 had 1 / 1 / 1 / 1 / 1 / 1 / 1 / 1 / 1 / 1	e 14%-ipage 0 12000 0 20000 0 00000 0 00000 100000 100000 100000 100000 100000 100000 100000 100000 100000 100000 100000 100000 100000 100000 1000	18g 11ne 6	*		,
	(1) 		13 14 - 15 - 19 - 19 - 19 - 19 - 19 - 19 - 19		THE T STATE	
						TECHNICAL FIELDS SEARCHED (HT.CLS)
						H04J H04L H04B
					:	
					:	
	The present search rep	port has been draw	n up for all claims			
	Place of search THE HAGUE		Date of completion of		Cha	Examiner
X : par	THE HAGUE CATEGORY OF CITED DOC Control of the same attacks and the same attacks are same attacks.	ne I with another	E : earl after D : doc	ory or principle user patent document cated in the	nderlying the i	uvet, C invention shed on, or

ANNEX TO THE EUROPEAN SEARCH REPORT ON EUROPEAN PATENT APPLICATION NO.

Fig. 10 8906

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

A GO BOOK SOLEN


Patent document cited in search report	Publication date	raigill (anill)	Publication date
WO 9605668 A	22-02-1996	US, 5550809 AU 3322095 BR 9508876 CA 2197640 CN 1159872 EP 0776555 FI 970637	A 07-03-1996 A 30-12-1997 A 22-02-1996 A 17-09-1997 A 04-06-1997
‡	· !	JP 10507322 NO 970667 US 5742678 US 5771288	A 16-04-1997 A 21-04-1998
	l		
FURIT TOP (A)		e e	
· ·			3
			:
; ;	; ;		:
tion of the second of the seco	eran er		a marina yan
The second secon	Arrana (CV), control of war 2000 to war 20	A THE COLUMN TO	و معووم عدي ا

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

The second second Contract to the contract of the second section 一年中 神 建铁 用水 医颗粒 医医乳浆 医抗性病 在一直的研究。如此, State of the state of the state of enning the fit the common or an amount of the The Y. Als. 1. 14. 5 % 44-47 MWT 1 NET The manufacture of the Sa had en mocoti tel (A) (1, 155 S.) 3. 18 3. 15 8 3 电神经数点 心定 15 00 03 W. MENTS & C.A. 三基本键 计符号 计磁放射 化碱进汽车机物物 新生色形成 AMERICAN SERVICES OF THE SERVI nothing to the arm term . Chare & Gar ending states The same of the sa Commence of the second कर १८ के अधिकार है की अधिकार अभीदर्भ भी $\label{eq:continuous_problem} \varphi_{t,q} = \varphi_{t,q} - \varphi_{t,q}^{-1/2} \cdot Q_{t}^{2} \varphi_{t}^{-1/2} + \varphi_{t}^{-1/2}$

নি ক্ষেত্ৰ কৰিছে কৰা কৰিছে লোক কৰিছে কৰিছে কৰিছে কৰিছে কৰিছে কৰিছে কৰিছে কৰিছে লোক কৰিছে । বাংলাক কৰিছে বাংলাক সমুদ্ধ কৰিছে সংস্থানিক কেন্দ্ৰ কৰিছে কৰিছে কৰিছে কৰিছে কৰিছে সমুদ্ধিক সমুদ্ধিক সমুদ্ধিক সমুদ্ধিক সমুদ্ধিক সমুদ

And the second of the second o



\$ 1.5